(51) International Patent Classification⁷: H04B 7/00

(21) International Application Number: PCT/EP00/12269

(22) International Filing Date: 6 December 2000 (06.12.2000)

(25) Filing Language: English

(26) Publication Language: English

(71) Applicant (for all designated States except US): NOKIA CORPORATION [FI/FI]; Keilalahdentie 4, FIN-02150 Espoo (FI).

(72) Inventors; and
(75) Inventors/Applicants (for US only): HOTTINEN, Ari [FI/FI]; Ristiniementie 4 o 30, FIN-02320 Espoo (FI). WICHMAN, Risto [FI/FI]; Viipurinkatu 10 A 20, FIN-00510 Helsinki (FI). TIRKKONEN, Olav [FI/FI]; Puroniitynpolku 5 A 6, FIN-00720 Helsinki (FI).

(74) Agent: COHAUSZ & FLORACK; Kanzlerstrasse 8a, 40472 Düsseldorf (DE).

(81) Designated States (national): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CR, CU, CZ, DE, DK, DM, DZ, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, TZ, UA, UG, US, UZ, VN, YU, ZA, ZW.

(84) Designated States (regional): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG).

Published:
— without international search report and to be republished upon receipt of that report

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: METHOD FOR CONTROLLING THE WEIGHTING OF A DATA SIGNAL IN THE AT LEAST TWO ANTENNA ELEMENTS OF A RADIO CONNECTION UNIT, RADIO CONNECTION UNIT, MODULE AND COMMUNICATIONS SYSTEM

(57) Abstract: The invention relates to a method for controlling the weighting of a data signal in the at least two antenna elements of a first radio connection unit of a radio communications system, which data signal is to be distributed for parallel transmission to a second radio connection unit to at least two beams. In order to improve such a method, it comprises: determining in the second radio connection unit a weight information enabling the first radio connection unit to determine the sets of weights for suitable beams for transmission and transmitting it to the first radio connection unit; and distributing the data signal in the first radio connection unit to those sets of weights and transmitting the data signals simultaneously via the formed beams. Alternatively or additionally, the second unit determines the number of beams to be used and informs the first unit about it. The invention equally relates to corresponding radio connection units, radio connection unit modules and radio communications systems.

Method for controlling the weighting of a data signal in the
at least two antenna elements of a radio connection unit,
radio connection unit, module and communications system

FIELD OF THE INVENTION

The invention relates to a method for controlling the
weighting of a data signal in the at least two antenna
elements of a first radio connection unit of a radio
communications system, which data signal is to be
distributed to at least two beams for parallel transmission
of the data signal in at least two at least partly different
streams to a second radio connection unit with at least one
antenna element, the beams being formed by weighting the
data signal in the antenna elements with a set of weights
for each beam. The invention equally relates to a radio
connection unit, a radio connection unit module and a radio
communications system to be employed for such a method.

BACKGROUND OF THE INVENTION

It is known from wireless communications systems of the
state of the art to transmit data signals between two radio
connection units, in particular from a base station to a
terminal, in parallel via several transmit antenna elements.
When using multiple antennas with adapted transmission and
detection techniques, the spatial dimension can be exploited

at the terminal and the spectral efficiency of fading
wireless channels can be increased significantly compared to
conventional single antenna links. A terminal receiving
signals from such a transceiver can be designed to
distinguish several channels, if they are sufficiently
uncorrelated.

The document "Link-Optimal BLAST Processing With Multiple-
Access Interference" by F.R. Farrokhi, G.J. Foschini, A.
Lozano, R.A. Valenzuela, Bell Laboratories (Lucent
Technologies) in IEEE Vehicular Technology Conference,
Boston, Massachussets, USA, Sept. 24-28, 2000, proceeds from
a wireless communications system with antenna arrays at
both, transmitter and receiver. The system transmits
parallel data streams simultaneously and in the same
frequency band, using the multiple antennas. With rich
propagation, the different streams can be separated at the
receiver because of their distinct spatial signatures. It is
proposed to make the channel and the interference covariance
available to the transmitter. The transmitter finds the
channel eigenmodes in the presence of the interference and
sends multiple independent data streams through those
eigenmodes. The total transmitted power is distributed among
the eigenmodes according to an optimal water-fill process.
Thereby, the maximised capacity is supposed to be achieved.
The method, as described above, always assumes that the
receiver has at least two antenna elements. Preferably, in
the aforementioned concept, the number of transmit and
receive elements is the same.

The parallel transmission via a plurality of antenna elements in transceiver and terminal enables a reduction of Eb/No (Eb = energy per bit; No = noise power density per Hz) requirements for achieving data rates associated with higher order constellations like 8PSK, 16QAM, or 64QAM. Moreover, it enables the expansion of the number of rate options for adaptive modulation and coding (AMC) and an increase of the maximum rate.

SUMMARY OF THE INVENTION

It is an object of the invention to provide a further improved method for controlling the weighting of a data signal in the at least two antenna elements of a transceiver of a wireless communications system which allows for high data rates in the downlink matched to channel conditions.

This object is reached on the one hand by a first method for controlling the weighting of a data signal in the at least two antenna elements of a first radio connection unit of a radio communications system, which data signal is to be distributed to at least two beams for parallel transmission of the data signal in at least two at least partly different streams to a second radio connection unit with at least one antenna element, the beams being formed by weighting the data signal in the antenna elements with a set of weights for each beam, the method comprising:
-   determining in the second radio connection unit a weight information enabling the first radio connection unit to

determine the sets of weights for at least two suitable
beams for transmission of a data signal from the first
radio connection unit to the second radio connection
unit;

- transmitting the determined weight information to the
  first radio connection unit; and

- distributing the data signal in the first radio
  connection unit to at least two sets of weights
  determined from the received weight information and
  transmitting the data signals simultaneously via the at
  least two formed beams.

With regard to this first method, the invention proceeds
from the idea that the second radio connection unit is in
possession of the most comprehensive information relevant
for selecting suitable beams for transmission of the data
signal and for determining sets of weights for the selected
beams. It is therefore proposed to calculate all relevant
information needed for the weighting of the data signals in
the antenna elements of the first radio connection unit
already at the second radio connection unit. The feedback
information includes a weight information from which the
first radio connection unit can determine the set of weights
for each beam that is to be used for transmission of the
data signals from the first radio connection unit to the
second radio connection unit. Each feedback information
indicates the weighting of the data signal for each of the
different antenna elements of the first radio connection
unit. This way, the information needed for obtaining the
weight sets can be determined with the full information

present at the second radio connection unit, while only the
information needed is fed back to the first radio connection
unit.

It is to be noted that the feedback information can include
the set of weights for each selected beam, the first radio
connection unit only having to apply the received sets for
forming the selected beams. It is not required, however,
that the second radio connection unit determines and
transmits all sets of weights, if there exists an a priori
fixed or negotiated way of calculating multiple weights from
a single feedback known to both, first and second radio
connection unit. Then, a reduced feedback information is
sufficient, which enables the first radio connection unit to
determine the necessary sets of weights. Therefore, the
second radio connection unit controls the parallel beams
with weight information either directly using explicit
feedback for all beams or implicitly using reduced feedback
and the knowledge of beam parameterisation at the first
radio connection unit.

On the other hand, the object is reached by a second method
for controlling the weighting of a data signal in the at
least two antenna elements of a first radio connection unit
of a radio communications system, which data signal is to be
distributed to at least two beams for parallel transmission
of the data signal in at least two at least partly different
streams to a second radio connection unit with at least one
antenna element, the beams being formed by weighting the

data signal in the antenna elements with a set of weights for each beam, said second method comprising:

- determining in the second radio connection unit the number of beams to be used for transmission of a data signal from the first radio connection unit to the second radio connection unit;
- providing the first radio connection unit with information about the determined number of beams; and
- distributing the data signal in the first radio connection unit to the number of beams corresponding to the number of beams determined in the second radio connection unit.

Just like in the first proposed method, in the second proposed method according to the invention, the second radio connection unit makes use of its knowledge in order to determine an information relevant for beamforming in the first radio connection unit and transmits this information to the first radio connection unit. The difference is that here, the information may include the number of beams that are to be formed by the first radio connection unit.

Both methods are aimed at controlling the weighting of a data signal that is to be divided, usually after encoding and modulation, into at least two parts for transmission. At least partly different symbols are therefore transmitted in parallel using the at least two formed beams, even though the symbols transmitted by the two beams do not have to be completely different.

The weight information for the selected beams and the number of beams respectively can be signalled to the first radio connection unit using any feasible technique known in the state of the art.

The transmitted data signals can be received at the second radio connection unit by one antenna element or by several antenna elements.

The above stated object of the invention is equally reached by a radio connection unit that can be used as first and/or as second radio connection unit, comprising means respectively for realising the methods according to the invention. Moreover, the object is reached by radio connection unit modules comprising means for realising the methods according to the invention in a first or second or a combined first and second radio connection unit. Finally, also a radio communications system with radio connection units suitable for realising the methods according to the invention reaches this object of the invention.

Preferred embodiments of the invention become apparent from the subclaims.

In the first method according to the invention, the second radio connection unit preferably determines the set of weights for at least two dominant downlink beams that are spatially sufficiently independent or uncorrelated for reception at said second radio connection unit. The sets of

weights for forming the downlink beams that are fed back to
the first radio connection unit can be calculated at the
second radio connection unit so that they enable an
efficient signal separation at the receiver. As an example,
if the two most dominant beams are highly correlated, the
first radio connection unit and the second radio connection
unit can use only one of them for an efficient parallel
transmission. In this case, only one of those most dominant
beams is used and in addition another dominant beam with a
smaller eigenvalue but which is sufficiently different from
the two most dominant beams. With sufficient information
about the beamforming at the first radio connection unit,
again, instead of all needed sets of weights only some
reduced weight information from which several sets of
weights can be determined can be transmitted to the first
radio connection unit as feedback information.

In a further preferred embodiment of the first of the
proposed methods, the second radio connection unit not only
determines the downlink beams and the corresponding weight
information indicating the sets of weights that are to be
used for multiple transmission, but also the data rates to
be used for each of the selected beams. The data rates are
determined in the second radio connection unit according to
the characteristics of the received channels and information
about the determined data rates is transmitted to the first
radio connection unit. This means, the data rate mapping to
multiple beams is done at least partially using a second
radio connection unit to first radio connection unit
feedback. Thereby, the downlink data rate using multiple

transmit beams or weight sets can be maximised. In order to
be able to assign the data rates, the signal-to-noise ratio
(SNR) or signal-to-interference ratio (SIR), or signal-to-
noise-plus-interference ratio (SINR) of the different
channels can be evaluated. Moreover, with correlated
channels, the data rate should typically be reduced
regardless of the number of transmit or receive antenna
elements. The data rates can be determined in a way that the
total data rate remains constant. Advantageously, however,
the total data rate is determined in a way that it coincides
with a data rate requested by the terminal and that the
associated transmission power supports the quality-of-
service (QoS) criteria (e.g. SIR, SNR, SINR, Bit Error Ratio
BER, Frame Error Rate FER, Outage) set for the transmitted
service by the terminal.

The information about changes in the data rates transmitted
from the second to the first radio connection unit can be
differential or absolute. In the first case, e.g. only a
requested increase or decrease in a data rate has to be
indicated in the feedback, while in the second case, the
data rate can change arbitrarily, but more feedback is
required.

The determination of multi-rate beams is preferably done in
the second radio connection unit by taking into account the
effective signal-to-noise ratio for parallel beams and by
using in addition the knowledge of the receiver structure in
the second radio connection unit. For example, some
receivers can be better suited for mitigating inter-beam

interferences than others. Furthermore, the inter-beam
interference can be optimised when controlling jointly the
transmit powers, weight coefficients and data rates.

In an equally preferred embodiment of the first method
according to the invention, the second radio connection unit
determines alternatively or in addition to the data rate
distribution an advantageous power distribution over the
selected downlink beams. Like the data rates, also the power
distribution is determined in the second radio connection
unit according to the characteristics of the received
channels. The second radio connection unit transmits
information about this distribution to the first radio
connection unit for controlling the antenna elements
accordingly. Equivalent as for the data rates, the total
power over all used beams can be kept constant.

The optimal power allocation can be determined in a way that
the desired SIR is met after the sets of weights have been
fixed. A downlink power assignment for the power of downlink
beams with fixed beam coefficients from a base station to a
number of terminals is described in "Optimal downlink power
assignment for smart antenna systems" by Weidong Yang;
Guanghan Xu, in Acoustics, Speech and Signal Processing,
1998; Proceedings of the 1998 IEEE, Vol. 6, pp. 3337-3340.
This approach can be adapted for the first method of the
invention to be used to jointly determine the powers and the
QoS parameters for each of several parallel downlink beams
from a first radio connection unit to a given second radio
connection unit rather than for the power of downlink beams

from a base station to multiple users, where to each user
there is assigned one beam.

Alternatively, the transmit powers for the downlink beams
can be determined jointly with the determination of the set
of weights or corresponding weight information for the
optimal beams. In the document "Joint Optimal Power Control
and Beamforming in Wireless Networks Using Antenna Arrays",
by F. Rashid-Farrokhi, L. Tassiulas, and K. J. Ray Liu, IEEE
Transactions On Communications, vol. 46, no. 10, October
1998, pp. 1313-1323, an algorithm is provided for computing
transmission powers and beamforming weight vectors, such
that a target SINR is achieved for each link from one base
station to a plurality of terminals with minimal
transmission power. In the documents, it is proposed that
for a fixed power allocation, each base station maximises
the SINR using the minimum variance distortionless response
(MVDR) beamformer. Next, the mobile powers are updated to
reduce the cochannel interference. This operation is done
iteratively until the vector of transmitter powers and the
weight coefficients of the beamformers converge to the
jointly optimal value. Assuming that at least two spatial
channels have been estimated for the second radio connection
unit, the sets of weights and the power optimisation
techniques proposed by Farrokhi et al. can be used in the
first method of the invention to determine multiple beams
for parallel transmission from the first to the (single)
second radio connection unit instead of from a base station
to multiple users. As a result, the second radio connection
unit has all relevant information for optimising the beams

and for distributing the signals to at least two parallel
beams.

Furthermore, for determining the at least two suitable
downlink beams, channel information and/or interference
information can be used in the second radio connection unit.
A possibility for determining an interference covariance
matrix that can be used in the method according to the
invention to calculate the optimal eigenvectors at the
second radio connection unit, is described e.g. in "Maximum
Likelihood Multipath Channel Parameter Estimation in CDMA
Systems", by C. Sengupta, A. Hottinen, J.R. Cavallaro, and
B. Aazhang, 32nd Annual Conference on Information Sciences
and Sysetms (CISS), Princeton, March 1998.

The weight information, which may include the sets of
weights, and/or the data rates and/or the power distribution
can be determined in the second radio connection unit either
based on short term variations of the received channels or
based on the stationary structure of the received channels
or on a combination of both. In a slowly fading channel,
short term variations can be used to determine the weight
information and related data rate information.
Alternatively, short term information can be used for
signalling only the data rate and/or the power information
for beams that are determined by using the stationary
structure of the received channels. With short term
variations, high resolution beams can be calculated such
that the instantaneous data rate is maximised. This, of
course, works only in slowly fading environments.

In case the stationary structure of the received channels is used for determining the weight information for the at least two downlink beams, preferably the eigenvectors of the spatial signal covariance matrices are calculated. However, the weight information for the preferred beams can be calculated in any other suitable way. For example, the subspace weight vectors can be tracked with a singular value decomposition and subspace tracking, which does not require the calculation of the correlation matrix and a subsequent eigenvalue decomposition. Such a tracking can be taken e.g. from "Solving the SVD Updating Problem for Subspace Tracking on a Fixed Sized Linear Array of Processors" by C. Sengupta, J.R. Cavallaro, and B. Aazhang, International Conference on Acoustics, Speech, and Signal Processing (ICASSP), Volume 5, pp. 4137-4140, Munich, April 1997. Alternatively, an independent component analysis can be applied, as described e.g. by J.F. Cardoso and P. Comon in: "Independent Component Analysis, a Survey of Some Algebraic methods", Proc. ISCAS Conference, volume 2, pp. 93-96, Atlanta, May 1996. In this case, the beams transmitted in parallel are typically non-orthogonal.

In a preferred embodiment of the second method according to the invention, the second radio connection unit determines the number of beams to be used for transmission of a data signal from the first radio connection unit to the second radio connection unit based on channel and/or interference information.

As one possibility for transmitting the information about
the determined number of beams in the second method
according to the invention, the determined number of beams
to be used for transmission of a data signal from the first
radio connection unit to the second radio connection unit
can simply be indicated by the number of beams that are
transmitted from the second radio connection unit to the
first radio connection unit. As mentioned above, the number
of beams can also be included in the number of sets of
weights determined and transmitted as proposed for the first
method according to the invention.

In the second method according to the invention, the first
radio connection unit can signal in addition to the number
of beams beam indices selected for transmission, enumerated
in some way.

The first method according to the invention can, but does
not necessarily, include the second method according to the
invention. That means, in the first method according to the
invention, the number of beams to be used can be determined
first in the second radio connection unit and for this
number of beams, sets of weights are determined and
transmitted to the first radio connection unit, or the
number is included in the weight information if this weight
information does not include the complete set of weights to
be used. Alternatively, the number of sets of weights
determined in the second radio connection unit can be fixed.

In both methods according to the invention, the second radio
connection unit should recover the data signals distributed
to the at least two beams in the first radio connection unit
and transmitted in at least two at least partly different
streams to the second radio connection unit. This means, the
parts transmitted by different streams have to be combined
again in the correct symbol/bit order.

In a preferred embodiment of both methods according to the
invention, the first radio connection unit transmits weight
information used for beamforming to the second radio
connection unit and the second radio connection unit uses
the received weight information for evaluation of the
received data signals. With this knowledge, the quality and
the speed in determining information to be transmitted to
the first radio connection unit can be improved. In an
alternative embodiment for the first method of the
invention, the second radio connection unit can make use of
its own knowledge included in the weight information
transmitted to the first radio connection unit for
recovering the data signals. In both embodiments, the second
radio connection unit can use the channel estimates obtained
for each antenna element, the transport format information,
and the used beam coefficients for each beam in order to
detect and decode the information most efficiently. The
receiver can use any techniques known in the art to that
end, including joint detection, joint decoding, joint
detection/decoding and channel estimation implemented either
iteratively, or non-iteratively. As an example, techniques

analogous to those described in A. Hottinen and O. Tirkkonen, "Iterative decoding and detection in a high data rate downlink channel," Proc. NORSIG, Kolmorden, Sweden, June 2000, can be used.

In both methods of to the invention, the first radio connection unit can be a base station and the second radio connection unit a terminal, the formed beams being downlink beams. Equally, the first radio connection unit can be a terminal and the second radio connection unit a base station, the formed beams being uplink beams. Consequently, the methods can also be employed with a base station and a terminal which can both form the first radio connection unit and the second radio connection unit.

The proposed method is of particular advantage when used in FDD systems.

The first and second radio connection units are preferably base stations and user equipments, where base station and user equipment can include either only means for one of the first and the second radio connection unit or means for both.

DETAILED DESCRIPTION OF THE INVENTION

In the following, the invention is explained in more detail for three embodiments.

All three embodiments of a method according to the invention
relate to a WCDMA FDD wireless communications system, in
which data signals are to be transmitted with a very high
data rate from a base station to a user equipment. The base
station comprises an antenna array with M antenna elements
and the user equipment comprise an antenna array with N
antenna elements. The data signals are transmitted in
parallel and with the same frequency, but with different
beams from the base station to the user equipment.

The beams are formed by assigning a different set of weights
to the data signals assigned to one beam, the set of weights
determining the weighting with which each data bit is
transmitted from each antenna element of the base station.
To each beam, there is assigned a data rate with which bits
are to be transmitted and an output power. The number of
beams to be used, the beam weights, the data rates and the
power for the selected beams are determined in the user
equipment.

The first embodiment of a method according to the invention
is proposed for correlated spatial channels. A specific
parameterised weight set for the base station antenna array
is assumed. That is, it is assumed that the base station has
an uniform linear array (ULA); the antennas have equal
spacing, which spacing is small enough to allow significant
(but not necessarily close to unit) correlation between
neighbouring antennas. Under those assumptions, a particular
parameterised beam-forming concept is used at the user

equipment in which the transmit weight/array vector, parameterised by θ, is given by:

$$w(\theta) = \left[1, e^{j\theta}, \ldots, e^{j(M-1)\theta}\right]^{T} / \sqrt{M}$$

The feedback can be calculated e.g. using the eigenvectors corresponding to the two largest eigenvalues of the channel matrix $H^{H}H$, where $H=(h_{1}, \ldots, h_{M})$ and where h_{m} is the impulse response between the m^{th} array element and all antennas of the user equipment. When denoting these vectors by e_{max_i} (i = 1,2) and solving

$$\theta^{*} = \operatorname*{argmax}_{\theta} \left\| w(\theta)^{H} e_{max\_i} \right\|^{2} ,$$

the phases at the transmit element m are $w_{m} = e^{j(m-1)\theta^{*}}$.

If the user equipment finds it advantageous, some (not necessarily orthogonal) linear combinations of the eigenvectors may be used as a basis for directing the beams from the ULA, instead of the eigenvectors e_{max_i}. For example, if the data rates that may be assigned to the beams are such that the beam with the highest eigenvalue may support more data than can be transmitted with the highest supportable data rate, the user equipment may choose to select correlating beams, where a suitable mixture of orthogonal beams are used to reach the maximal data rate with an acceptable Quality of Service.

The set of parameters θi for parallel transmission is fed
back to the base station applying e.g. Mode 1 feedback
signalling. In Mode 1, the feedback bit signals in
successive slots the real and the imaginary parts of the
feedback weights, or the angular parameters θi in this case.
It is also possible to parameterise the gains of the
antennas with one or more parameters. One parameterisation
would be to have the gains linearly increasing or decreasing
along the linear array. Other parameterisation would enhance
or suppress the central antenna elements, or every second
element. If antenna gains are parameterised, the
maximisation above chooses the best angular and gain
parameters to match the eigenvectors. This information can
be transmitted e.g. by closed-loop Mode 2 signalling. In
closed-loop Mode 2, the feedback weight is signalled as a
Gray coded message with 3 phase bits and 1 gain bit. The
gain bit, transmitted every fourth slot, selects the
relative gain between the two transmit elements. Here, Mode
2 signalling would convey information of the angular
parameter θi in the phase bits, and one gain parameter in
the gain bit.

In addition, the feedback from the terminal to the
transmitter can be reduced, if the terminal knows the method
the transmitter uses in determining the coefficients for the
parallel beams. For example, it is possible that the
terminal sends the coefficients or parameters for one beam
only, and the base station then determines two or more
parallel beams using $w(\theta-\Delta)$ and $w(\theta+\Delta)$, where Δ is a priori

fixed or negotiated between the transmitter and the terminal, and where θ is the parameter for the two beams. Then, the terminal can optimise θ jointly for $w(θ-Δ)$ and $w(θ+Δ)$, so that there are two parameterised beams transmitted, but with only one feedback signal (θ). This generalises naturally to multiple parallel beams and different ways to calculate the multiple parallel beams from single feedback are possible.

In addition to the weight information, the user equipment determines the data rate to be used by each selected downlink beam. The data signal is to be distributed across the different downlink beams such that the target data rate R is met with minimal transmission power. This target rate may be chosen by the user equipment based on the channel and interference information available. The user equipment therefore assigns to N possible, not necessarily orthogonal beams, the data rates R1 to RN in a way that R = R1 + R2 + ... + RN = const. To this end, the signal-to-noise ratio SNR of the selected beams is evaluated. The selected dominant beam with the highest SNR is assigned the highest data rate and the selected dominant beam with the lowest SNR is assigned the lowest data rate. In addition, the correlation between the channels are taken into account. With high correlation, the data rate per selected beam is reduced, as the supportable (target) data rate has to be decreased. The data rates for the selected downlink beams are contained in additional feedback from the user equipment to the base station.

Equally included in such an additional feedback from the user equipment to the base station is information on the best power distribution for the different selected beams. The power can be assigned by the user equipment in a way that the total output power of the base station is constant, or minimised for a given data rate and quality of service requirement. Also for determining the power distribution, the channel characteristics are evaluated. For example, the lowest output power can be assigned to the selected dominant beam with the highest SNR. Transmitting information about the power distribution of different beams can be advantageously combined with transmitting the phase parameters θ_i, in feedback Mode 2 signalling. Now, the gain bit would indicate the relative gain of the beam in question, and the phase bits would convey information about the angular parameters θ_i. Similarly, data rate information can be indicate by the gain bit in Mode 2 signalling.

The processes of choosing the data rates and choosing the power distribution can in some cases be considered complementary, i.e. the effect of using one may be partly generated by using the other.

The base station receives from the user equipment the feedback signals with a set of weights, the data rate and the output power for each selected downlink beam. These feedback information enables the base station to distribute, weight and transmit the data signals in the manner that was

determined by the user equipment to be most suitable in the
present situation.

The data signals to be transmitted by the base station are
split in the base station to multiple downlink beams after
channel encoding so that different encoded bits are
transmitted from different beams with the assigned power.
For coding, e.g. Turbo coding is used and the bits are
sequentially sent via the different beams, taking into
account the different assigned data rates R1 to RM.
Moreover, the bits are suitably interleaved across the
spatial channels so that even if one channel or beam has a
very low SNR, the data can be decoded. For example, random
interleaving, or some optimised interleaving can be used. As
an example, with rate 1/3 Turbo encoder that provides
systematic bit (x0), parity bit 1 (x1) and parity bit 2
(x2), we can transmit x0 through at least two beams, x1
through beam 1 and x2 through beam 2. Thus, the encoded
signal is distributed in at least two beams, with at least
partially different contents. Each beam is formed by
weighting the supplied encoded data bits in the antenna
elements with the corresponding set of weights, which
includes weight information for each antenna element for the
specific beam. At the terminal, the different parts of the
data signals distributed to the different beams are combined
again in order to obtain the correct symbol or bit order for
channel decoding or for any other following receiver stage.

The second embodiment of the invention is based on an
eigenanalysis of the long-term spatial-temporal covariance

matrices estimated from the dominant
terminal that has N receive antenna
is especially suited for deciding t]
when correlated spatial channels are

The eigenbeams with the largest eige
the largest average SNR are determir
temporal correlation matrix. The don
determined by the eigenanalysis are
station as sets of weights for downl
determined weights are fed back to t
step, this process takes place rougl
scale as the physical movement of th
forming of eigenbeams has been descr
loop Tx diversity concept (eigenbeam
WG 1, TSGR1#14(00)0853 Meeting #14,
Finland, by Siemens for selecting di
beams.

Before or in parallel with transmitt
orthogonal pilot sequence is transmi
station antenna element to the user
received signals, the user equipment
long term spatial covariance matrix
the dominant temporal taps. In the p
than one receiving antenna element i
equipment, the dimension of the corr
typically increased as compared to o
element. Alternatively, the dimensio
regardless of the number of receive

aps with a
his approach
beams to use

therefore
spatial-
ectors
the base
ng. If the
on step by
time
it. Such a
ed closed
TSG RAN
Oulu,
ission

s, an
base
the
imate the
R_n, of
ere more
ser
s is
tenna
le same

latter case the receiver operations are simplified, and the
correlation matrix for signals and channel coefficients
received at different or selected receive antenna elements
is given by

R= H^H * H   with H = [h_1 h_2 ...h_M]

where M is the number of transmit antenna elements and where
h_1 (l=1...M) is a (NxL)x1 vector, a concatenation of N
impulse response vectors of length L, where N is the number
of receive antennas. For obtaining the weight vectors needed
for beam forming, the terminal calculates two different
vectors from this matrix R, e.g. the eigenvectors
corresponding to the two largest eigenvalues of the matrix.

The aforementioned method averages the contributions of each
path and receive antenna when calculating the correlation
matrix, and subsequently for determining the transmit beam
or beams based on the correlation matrix. Instead, it is
possible to determine the transmit beam coefficients for
each or for selected delay paths, or for selected receive
antennas. To this end, multiple correlation matrices are
calculated, where for calculating each correlation matrix a
different combination of rows from channel matrix H is
selected (i.e. a different set of row indices is selected
when calculating the correlation matrix). Then, multiple
weighting coefficients can be calculated, one corresponding
to each row index set. By selecting suitable rows, the
terminal can calculate weighting coefficients in a way that
different parallel beams are optimised for different receive

antennas or different multipath delays, or a combination of
the two. Furthermore, the terminal can take into account the
interference between the beams, thus effectively optimising
the Signal-to-Interference ratio, rather than just the
signal power. Notice that here it is sufficient for the
terminal to have only one receive antenna, as long as there
are at least two delay paths between the transmitter and the
terminal.

Long-term properties can be exploited by calculating the
weighting coefficients. Assume now that h_n is an M-
dimensional vector corresponding to the n^{th} dominant tap,
between M transmit elements and N receive antenna elements
at delay path n. The long term channel properties change
slowly over time, therefore a forgetting factor ρ is applied
to the long term spatial covariance matrix of the n^{th}
dominant temporal tap with the equation:

$$R_n(i) = \rho R_n(i-1) + (1-\rho) h_n(i) h_n^H(i),$$

where i denotes the slot number and h_n the vector of spatial
channel estimation of the n^{th} temporal tap. By forming the
eigenvectors, a decorrelation of the beamforming vectors can
be achieved, and thereby a reduction in dimension for
subsequent short-term processing and an improved short-term
channel estimation at the user equipment enabled by an
increase in diversity and antenna gain/interference
suppression.

Proceeding from the estimated covariance matrices R_n, the terminal performs an eigenanalysis in order to determine the eigenvectors with the equation:

$$R_n W_n = W_n \Theta_n$$

for each dominant temporal tap. The eigenvectors to be found are columns of W_n. Since the matrix Θ_n, which comprise the eigenvalues of matrices R_n, is diagonal by definition, transmission on different eigenbeams leads to uncorrelated fast fading. The diagonal entries of the matrix Θ_n indicate the long-term SNR of each beam. Here, a number of weighting vectors are defined, corresponding to the dominant eigenbeams, based different delay paths. Alternatively, the correlation matrix can be estimated for any other combination of row indices of H. For example, if all rows of H are selected, we need to track only one correlation matrix (average over multiple delay paths or receive antennas) and find at least two dominant eigenvectors or beams from a single matrix. The decision which delay paths and receive antenna paths are used can depend also on the receiver structure. However, the particular way the terminal decides to calculate the long term coefficients need not typically be known by the transmitter. The transmitter only needs to know the actual weighting coefficients that are applied in the transmitter in order to form the at least two beams.

With the calculation of the eigenvectors of the correlation matrices, an automatic adjustment to various propagation

environments (spatially correlated or uncorrelated, frequency selective or non-selective) becomes possible. If the channel is spatially correlated, the channel can accurately be described by a small number of weighted eigenbeams. If, on the other hand, the channel has a spatial correlation of zero, no long-term spatial channel information can be exploited and each eigenvector addresses only one antenna element. Thus the user equipment determines from the eigenvalue spread the number of sufficiently independent spatial channels and signals the weight sets for the corresponding downlink beams to the base station. As in the first embodiment, the selected beams may be intentionally correlating, to fully exploit the capacity of the channel.

The sets of weights determined for forming the downlink beams are chosen in a way that they enable an efficient signal separation at the receiver. If the most dominant beams are highly correlated, the transceiver or the terminal can efficiently use only one of them for parallel transmission. In this case, in addition to one of those most dominant beams, another dominant beam with a smaller eigenvalue but which is sufficiently different from the two dominant beams, or a suitable linear combination of beams, is selected.

The data rates and the power used for the different selected downlink beams are determined in the user equipment and transmitted as separate feedback information to the base station, as described with reference to the first

embodiment. Also the coding and interleaving of the data
signals that are to be transmitted is carried out as
described with reference to the first embodiment.

A third embodiment of a method according to the invention
can be applied in cases where there are no long term spatial
correlations.

The antenna elements are rather uncorrelated and the fading
process may be rather fast. The only slowly changing
characteristic is the rank of the channel matrix $H^H H$, i.e.
the number of non-zero eigenvalues. With a frequency
proportional to the expected or actual coherence time of the
channel, the user equipment selects at least two beams that
are linearly dependent on the eigenvectors related to at
least two of the strongest eigenvalues.

As in the first and the second embodiment, the beams need
not be orthogonal, and the feedback information may be
supplemented with information about data rates and/or
relative power distribution of the beams.

The weights corresponding to the selected beams are
transmitted to the base station. For this, e.g. Mode 1 or
Mode 2 signalling can be used, as explained in connection
with the first and the second embodiment.

In the whole, in all three embodiments, all necessary
processing for establishing an optimised feedback downlink
transmission in a base station with multiple transmission is

carried out in the user equipment, the base station only applying the received information.

Finally, it should be noted that the same methods may be applied to uplink transmissions in personal communication systems, or more generally, to any radio communication link with multiple input, multiple (or single) output channels, where a reciprocal channel exists that enables feedback signalling.

Claims

1. Method for controlling the weighting of a data signal in
    the at least two antenna elements of a first radio
    connection unit of a radio communications system, which
    data signal is to be distributed to at least two beams
    for parallel transmission of the data signal in at least
    two at least partly different streams to a second radio
    connection unit with at least one antenna element, the
    beams being formed by weighting the data signal in the
    antenna elements with a set of weights for each beam,
    the method comprising:
    -   determining in the second radio connection unit a
        weight information enabling the first radio
        connection unit to determine the sets of weights for
        at least two suitable beams for transmission of a
        data signal from the first radio connection unit to
        the second radio connection unit;
    -   transmitting the determined weight information to the
        first radio connection unit; and
    -   distributing the data signal in the first radio
        connection unit to at least two sets of weights
        determined from the received weight information and
        transmitting the data signals simultaneously via the
        at least two formed beams.

2. Method according to claim 1, wherein the second radio connection unit determines a weight information enabling the first radio connection unit to determine the set of weights for at least two dominant beams that are spatially sufficiently independent for reception at said second radio connection unit.

3. Method according to one of the preceding claims, wherein the second radio connection unit determines the data rate to be used for each of the determined beams according to the channel characteristics of said beams and transmits information about the data rates to be used to the first radio connection unit.

4. Method according to claim 3, wherein the second radio connection unit determines the data rates to be used for the at least two determined beams in a way that the total data rate is fixed.

5. Method according to claim 3, wherein the second radio connection unit determines the data rates to be used for the at least two determined beams in a way that the total data rate is met with minimal transmission power.

6. Method according to one of the preceding claims, wherein the second radio connection unit determines the power to be used for the at least two determined beams according to the channel characteristics and transmits information with the power to be used to the first radio connection unit.

7. Method according to claim 6, wherein the second radio connection unit determines the power to be used for the at least two determined beams in a way that the total power is constant.

8. Method according to one of the preceding claims, wherein channel and interference information is used in the second radio connection unit for determining the weight information enabling the determination of the sets of weights for the at least two suitable beams.

9. Method according to one of the preceding claims, wherein the short term variations in the received channels are evaluated in the second radio connection unit for determining the weight information and/or the data rates and/or the power to be used for each of the at least two suitable beams.

10. Method according to one of the preceding claims, wherein the stationary structure of the received channels is evaluated in the second radio connection unit for determining the weight information and/or the data rates and/or the power to be used for each of the at least two suitable beams.

11. Method according to claim 10, wherein the weight information is determined by an eigenanalysis of spatial covariance matrices representing the stationary structure of the received channels.

12. Method according to one of the preceding claims, wherein the stationary structure of the received channels is used in the second radio connection unit for determining the weight information and wherein short term variations in the received channels are used in the second radio connection unit for determining the data rates and the power to be used for said beams.

13. Method according to one of the preceding claims, wherein the second radio connection unit recovers the data signals distributed to the at least two beams in the first radio connection unit and transmitted in at least two at least partly different streams to the second radio connection unit.

14. Method according to claim 13, wherein the second radio connection unit uses the weight information transmitted to the first radio connection unit for recovering the data signals.

15. Method according to claim 13, wherein the first radio connection unit transmits a weight information from which the second radio connection unit can determine the sets of weights used for transmission of the data signals to the second radio connection unit and wherein the second radio connection unit uses the weight information for recovering the data signals.

16. Method according to one of the preceding claims, wherein the second radio connection unit determines the number of beams to be used for transmission, the transmitted weight information comprising information about the number of beams to be used.

17. Method according to claim 16, wherein the second radio connection unit determines the number of beams to be used for transmission of a data signal from the first radio connection unit to the second radio connection unit based on channel and/or interference information.

18. Method for controlling the weighting of a data signal in the at least two antenna elements of a first radio connection unit of a radio communications system, which data signal is to be distributed to at least two beams for parallel transmission of the data signal in at least two at least partly different streams to a second radio connection unit with at least one antenna element, the beams being formed by weighting the data signal in the antenna elements with a set of weights for each beam, the method comprising:
   - determining in the second radio connection unit the number of beams to be used for transmission of a data signal from the first radio connection unit to the second radio connection unit;
   - providing the first radio connection unit with information about the determined number of beams; and

- distributing the data signal in the first radio connection unit to the number of beams determined in the second radio connection unit.

19. Method according to claim 18, wherein the second radio connection unit determines the number of beams to be used for transmission of a data signal from the first radio connection unit to the second radio connection unit based on channel and/or interference information.

20. Method according to claim 18 or 19, wherein the determined number of beams to be used for transmission of a data signal from the first radio connection unit to the second radio connection unit is indicated by the number of beams that are transmitted from the second radio connection unit to the first radio connection unit.

21. Method according to one claims 18 to 20, wherein the second radio connection unit recovers the data signals distributed to the at least two beams in the first radio connection unit and transmitted in at least two at least partly different streams to the second radio connection unit.

22. Method according to claim 21, wherein the first radio connection unit transmits a weight information enabling the second radio connection unit to determine the sets of weights used for transmission of the data signals to the second radio connection unit and wherein the second

radio connection unit uses the received weight information for recovering the data signals.

23. Method according to one of the preceding claims, wherein the first radio connection unit is a base station and the second radio connection unit a user equipment and wherein the formed beams are downlink beams.

24. Method according to one of the preceding claims, wherein the first radio connection unit is a user equipment and the second radio connection unit a base station and wherein the formed beams are uplink beams.

25. Use of a method according to one of claims 1 to 24 in a WCDMA FDD system.

26. Radio connection unit for a wireless communications system comprising at least two antenna elements and means for realising as first radio connection unit the method according to one of claims 1 to 24.

27. Radio connection unit for a wireless communications system comprising at least one antenna element and means for realising as second radio connection unit the method according to one of claims 1 to 24.

28. Radio connection unit for a wireless communications system comprising at least two antenna elements, and means for realising as first radio connection unit the method according to one of claims 1 to 24 as well as

means for realising as second radio connection unit the method according to one of claims 1 to 24.

29. Radio connection unit according to one of claims 26 to 28, wherein the radio connection unit is a base station.

30. Radio connection unit according to one of claims 26 to 28, wherein the radio connection unit is a user equipment.

31. Radio connection unit module comprising means for realising the method according to one of claims 1 to 24 in a radio connection unit for a wireless communications system to be used as first radio connection unit.

32. Radio connection unit module comprising means for realising the method according to one of claims 1 to 24 in a radio connection unit for a wireless communications system to be used as second radio connection unit.

33. Radio connection unit module comprising means for realising the method according to one of claims 1 to 24 in a radio connection unit for a wireless communications system to be used as first or second radio connection unit.

34. Radio connection unit module according to one of claims 31 to 33, wherein the radio connection unit module is a base station module or a user equipment module.

35. Radio communications system, comprising at least one radio connection unit with means for realising as first radio connection unit the method according to one of claims 1 to 24 and at least one radio connection unit with means for realising as second radio connection unit the method according to one of claims 1 to 24.

36. Radio communications system according to claim 35, wherein the radio connection units used as first radio connection unit are base stations and/or user equipments.

37. Radio communications system according to claim 35, wherein the radio connection units used as second radio connection unit are base stations and/or user equipments.

38. Radio communications system according to one of claims 35 to 37, wherein at least one of the radio connection units comprises means for realising the method according to one of claims 1 to 24 as both, first and second radio connection unit.

THIS PAGE BLANK (USPTO)

(51) International Patent Classification[7]: H04B 7/06

(21) International Application Number: PCT/EP00/12269

(22) International Filing Date: 6 December 2000 (06.12.2000)

(25) Filing Language: English

(26) Publication Language: English

(71) Applicant (for all designated States except US): NOKIA CORPORATION [FI/FI]; Keilalahdentie 4, FIN-02150 Espoo (FI).

(72) Inventors; and
(75) Inventors/Applicants (for US only): HOTTINEN, Ari [FI/FI]; Ristiniementie 4 o 30, FIN-02320 Espoo (FI). WICHMAN, Risto [FI/FI]; Viipurinkatu 10 A 20, FIN-00510 Helsinki (FI). TIRKKONEN, Olav [FI/FI]; Puroniitynpolku 5 A 6, FIN-00720 Helsinki (FI).

(74) Agent: COHAUSZ & FLORACK; Kanzlerstrasse 8a, 40472 Düsseldorf (DE).

(81) Designated States (national): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CR, CU, CZ, DE, DK, DM, DZ, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, TZ, UA, UG, US, UZ, VN, YU, ZA, ZW.

(84) Designated States (regional): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG).

Published:
— with international search report

(88) Date of publication of the international search report:
4 September 2003

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: METHOD FOR CONTROLLING THE WEIGHTING OF A DATA SIGNAL IN THE AT LEAST TWO ANTENNA ELEMENTS OF A RADIO CONNECTION UNIT, MODULE AND COMMUNICATIONS SYSTEM

(57) Abstract: The invention relates to a method for controlling the weighting of a data signal in the at least two antenna elements of a first radio connection unit of a radio communications system, which data signal is to be distributed for parallel transmission to a second radio connection unit to at least two beams. In order to improve such a method, it comprises: determining in the second radio connection unit a weight information enabling the first radio connection unit to determine the sets of weights for suitable beams for transmission and transmitting it to the first radio connection unit; and distributing the data signal in the first radio connection unit to those sets of weights and transmitting the data signals simultaneously via the formed beams. Alternatively or additionally, the second unit determines the number of beams to be used and informs the first unit about it. The invention equally relates to corresponding radio connection units, radio connection unit modules and radio communications systems.

INTERNATIONAL SEARCH REPORT

A. CLASSIFICATION OF SUBJECT MATTER
IPC 7   H04B7/06

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
IPC 7   H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, INSPEC, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category °	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	WO 00 72464 A (NOKIA NETWORKS OY ;WICHMAN RISTO (FI); HOTTINEN ARI (FI)) 30 November 2000 (2000-11-30) abstract	1,2,6,7, 9,13, 23-38
Y	page 1, line 13 -page 2, line 28 page 5, line 7-20 page 21, line 22 -page 22, line 17 figures 1,5	10,11
X	WO 00 36764 A (NOKIA NETWORKS OY ;WICHMAN RISTO (FI); HOTTINEN ARI (FI)) 22 June 2000 (2000-06-22) abstract page 4, line 2033 page 11, line 1 -page 12, line 6 page 14, line 5-24 figure 2A	1,8,9, 13-15, 23-38

-/--

[X] Further documents are listed in the continuation of box C.   [X] Patent family members are listed in annex.

° Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier document but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

"&" document member of the same patent family

Date of the actual completion of the international search	Date of mailing of the international search report
28 June 2001	2 8 JUNE 2001

Name and mailing address of the ISA	Authorized officer
European Patent Office, P.B. 5918 Patentlaan 2 NL - 2280 HV Rijswijk Tel. (+31-70) 340-2040, Tx. 31 651 epo nl, Fax: (+31-70) 340-3016	Helms, J

Form PCT/ISA/210 (second sheet) (July 1992)

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category °	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	WO 98 09381 A (UNIV LELAND STANFORD JUNIOR) 5 March 1998 (1998-03-05) abstract page 23; claim 12 figure 7 ---	1
Y	"Advanced closed loop Tx diversity concept (eigenbeamformer)", 3GPP TSG RAN WG 1, TSGR1#14(00)0853, 4.-7. July 2000, Oulu, Finnland, by Siemens XP002169992 cited in the application the whole document ---	10,11
A	FARROKHI F R ET AL: "Link-optimal BLAST processing with multiple-access interference" VEHICULAR TECHNOLOGY CONFERENCE FALL 2000. IEEE VTS FALL VTC2000. 52ND VEHICULAR TECHNOLOGY CONFERENCE (CAT. NO.00CH37152), VEHICULAR TECHNOLOGY CONFERENCE FALL 2000. IEEE VTS FALL VTC2000. 52ND VEHICULAR TECHNOLOGY CONFERENCE, BOSTON, MA, USA, 24-28, pages 87-91 vol.1, XP002170648 2000, Piscataway, NJ, USA, IEEE, USA ISBN: 0-7803-6507-0 cited in the application abstract page 87, left-hand column, paragraph 1 -right-hand column, paragraph 3 ---	1-17, 23-38
A	US 6 067 324 A (HARRISON ROBERT MARK) 23 May 2000 (2000-05-23) abstract ---	1-17, 23-38
A	EP 0 605 119 A (AT & T CORP) 6 July 1994 (1994-07-06) abstract -----	1-17, 23-38

BEST AVAILABLE COPY

3

Box I   Observations where certain claims were found unsearchable (Continuation of item 1 of first sheet)

This International Search Report has not been established in respect of certain claims under Article 17(2)(a) for the following reasons:

1. ☐ Claims Nos.:
   because they relate to subject matter not required to be searched by this Authority, namely:

2. ☐ Claims Nos.:
   because they relate to parts of the International Application that do not comply with the prescribed requirements to such an extent that no meaningful International Search can be carried out, specifically:

3. ☐ Claims Nos.:
   because they are dependent claims and are not drafted in accordance with the second and third sentences of Rule 6.4(a).

Box II   Observations where unity of invention is lacking (Continuation of item 2 of first sheet)

This International Searching Authority found multiple inventions in this international application, as follows:

see additional sheet

1. ☐ As all required additional search fees were timely paid by the applicant, this International Search Report covers all searchable claims.

2. ☐ As all searchable claims could be searched without effort justifying an additional fee, this Authority did not invite payment of any additional fee.

3. ☐ As only some of the required additional search fees were timely paid by the applicant, this International Search Report covers only those claims for which fees were paid, specifically claims Nos.:

4. ☒ No required additional search fees were timely paid by the applicant. Consequently, this International Search Report is restricted to the invention first mentioned in the claims; it is covered by claims Nos.:

   1-17, 23-38

Remark on Protest   ☐ The additional search fees were accompanied by the applicant's protest.

                           ☐ No protest accompanied the payment of additional search fees.

International Application No. PCT/EP 00 /12269

FURTHER INFORMATION CONTINUED FROM   PCT/ISA/ 210

This International Searching Authority found multiple (groups of)
inventions in this international application, as follows:

   1. Claims: 1-17, 23-38

   2. Claims: 18-22

Patent document cited in search report		Publication date	Patent family member(s)		Publication date
WO 0072464	A	30-11-2000	WO	0072464 A1	30-11-2000
			AU	2548200 A	12-12-2000
			AU	4144799 A	12-12-2000
			CN	1304587 T	18-07-2001
			WO	0072465 A1	30-11-2000
			EP	1097525 A1	09-05-2001
			NO	20010290 A	18-01-2001
WO 0036764	A	22-06-2000	FI	982715 A	16-06-2000
			AU	1984700 A	03-07-2000
			BR	9916239 A	04-09-2001
			EP	1131903 A2	12-09-2001
			WO	0036764 A2	22-06-2000
WO 9809381	A	05-03-1998	AU	4238697 A	19-03-1998
			EP	0920738 A1	09-06-1999
			EP	0931388 A2	28-07-1999
			JP	2001505723 T	24-04-2001
			WO	9809385 A2	05-03-1998
			WO	9809381 A1	05-03-1998
			WO	9809395 A1	05-03-1998
			US	6144711 A	07-11-2000
US 6067324	A	23-05-2000	CN	1307753 T	08-08-2001
			EP	1092273 A1	18-04-2001
			WO	0001078 A1	06-01-2000
EP 0605119	A	06-07-1994	US	5289499 A	22-02-1994
			CA	2109789 A1	30-06-1994
			EP	0605119 A2	06-07-1994
			JP	2780918 B2	30-07-1998
			JP	6303214 A	28-10-1994
			US	5394435 A	28-02-1995